

# HEOS Drive HS2



## WHOLE HOME AUDIO IN A SINGLE CHASSIS.

### NETWORKED MULTI-ROOM AMPLIFIER

The evolution continues with the HEOS Drive HS2, a network multi-room amplifier. The powerful 4-zone, 8-channel multi-room amplifier covers all HEOS zones with a single 2U tall, rack mountable chassis—ideal for custom installers.

The HEOS Drive is part of the HEOS multi-room sound system that enables you to enjoy your favorite music anywhere and everywhere around your home. By utilising an existing home network and the HEOS app for iOS, Android and Kindle Fire, you can explore, browse, and play music from your own music library. You can also stream online music services and thousands of internet radio stations.

This powerful 4 zone, 8 channel amplifier is a custom installers dream. With similar functionality to both the HEOS Amp and HEOS Link, you get 4 HEOS zones in a single 2U (3.5" tall) chassis. Powerfull class-D amplification, included rack mount ears, active cooling, reliable wired Ethernet input and pass-through and it's compact size, make the HEOS Drive the perfect choice for a whole-home distributed audio system.





## PERFECT SOUND MADE SIMPLE.

Designed by custom integration specialists for custom integration professionals, HEOS Drive HS2 is a unique 4 zone whole home audio distribution system with 8 channels of Class D amplification, all in a single 2U tall chassis that features both Dolby Digital and Dolby Digital+ decoding with stereo downmixing.

Rated at 60 watts per channel into each of the 8 channels (20Hz~20kHz, 0.05% THD, 8 ohms, All Channels Driven), 1 or 2 stereo amp pairs can be bridged for single channel high power output (130 watts), and the HEOS Drive HS2 features low impedance drive capability (4 ohms).

## KEY FEATURES

- Four independent, amplified HEOS zones
- 8 Channel Class D digital amplification; 60 Watts/ch (20Hz~20kHz, 0.05% THD, 8 ohms, All Channels Driven); 4 ohms compatible; bridge mode (130 Watts/ch)
- Pre-amp outputs for each zone
- Amazon Alexa voice integration
- Third Party Control Compatible
- Four x 12V Trigger Outputs
- Two Fiber Optic, two Digital Coax and four Analog Inputs (Matrix switching)
- Four USB Inputs
- Selectable Stereo/Mixed Mono Output
- Selectable High Pass/Low Pass Filters
- Two Ethernet Inputs
- Rack Ears Included
- 2U (3.5") Rack Height (with feet removed)
- Multi Voltage Power Supply
- Dolby Digital Decoding (Downmix to 2.0ch)
- 192/24 FLAC, ALAC, WAV, DSD 2.8MHz and 5.6MHz Playback

**JUKE!**



**MOOD:MIX**



## SPECIFICATIONS

### Class D Digital Amplification:

8 x 60 (20Hz-20kHz, .05% THD) watts (130W in bridge mode) of Class D digital amplification provide high efficiency, lowest distortion and widest dynamic range.

**Product Finish:** Black

**Power Supply:** 100~240 Volts AC, 50~60 Hz auto-switching

**Weight:** 7.2 kg

### Dimension in mm

**(W x H x D):** 88mm x 430mm x 402 mm (without rack ears)  
88mm x 483mm x 402 mm (with rack ears)

**Wired Connectivity:** Dual RJ-45 jack for connection to wired Ethernet

**Package Contents:** HEOS Drive HS2, AC power cord, Ethernet Cable, Quick Start Guide, 2 rack ears

[www.denon.co.uk/uk/heos](http://www.denon.co.uk/uk/heos)